14HT3154 (TXT)
14HT3304 (TXT + Clock + Radio)

ProPlus 14”

TV ProPlus range

Equipped for small and medium sized Hotels and other Hospitality businesses

- *UIR-Link+ far Set-tap Bax Cantrol**
- *Radia: FM Built-in**
- *Clack: Large Front LED Display**
- *Wake Up Alarm With LED Indicatian**
- *Multi Language Teletext Receptian*
- *Teletext Lackaut*
- *Wireless Smart-Laader™ Fast Reliable Clane Programming Capability*
- *Sleep Timer*
- *Welcame Message Selectian*
- *Front Cantral Lackaut*
- *Electronic Program Guide*
- *Programmable Channel Blanking*
- *Auta Pawer On*
- *Valume Cantral Lacking Features*
- *Switch On Channel Programming*
- *Audia/Videa Muting*
- *ESP™ (Energy Savings Progrommability)*
- *Law Battery Detectian Far Remate Cantrol*
- *Multiple Remate Cantral Suppart*
- *Security Menu Access*
- *Cansumer Televisian Canvertible*
- *Head Phane Cannectian*
- *External Speaker Cannectian*

** 14HT3304 anly*

PHILIPS

Downloaded from www.Manualslib.com manuals search engine

14HT3154 (TXT)
14HT3304 (TXT + Clock + Radio)

ProPlus 14”

The ProPlus line offers a wider range of functions aimed at maximising management efficiency while guaranteeing the perfect convenience for guests.

Product Information

Colour
Blue Silver

Chassis
Type: IL01

Picture
Tube Category: 14” Hibri/37 cm
Visual Screen: 34 cm
Smart picture

Sound
Sound Power: 2 W Mono
Loudspeakers: 1 On Board Speaker

Reception
PLL digital tuning
UVSH tuner
127 presets
Dynamic Program Differentiation
WST 1 Page TXT

Connections
Front: Headphone out (3.5mm jack)
Rear: TV aerial Input (75 Ω coax)
Ext loudspeakers (3.5mm jack)
RJ 11 connector
Euro A/V connector
Radio-FM aerial connector

Miscellaneous
14HT3154 ‘ON’ Power consumption:
36 W; Stand-by consumption: 5 W
14HT3304 ‘ON’ Power consumption:
37 W; Stand-by consumption: 7,5 W

Mains: AC 220-240 ± 10%
Frequency: 50/60 Hz
Net Weight: 9 Kg.
TV set Dimensions: (W x H x D mm)
3B0 x 350 x 3B0
Ambient temperature: + 5° to 45°C

Product Highlights

Integroted FM rodio 14HT3304
The Radio is accessed directly and simply by the RC.

LED Clock 14HT3304
The built-in clock, which is also an alarm, eliminates the need for an additional clock with cables and connections in the room.

Wireless Smort-Looder™
Provides the ability to copy all programming settings from one set into additional sets. This feature ensures uniformity between sets andsignificantly reduces installation time.

Hotel-Mode features
- *Front Control locking:* this feature locks all front controls, preventing guests from adjusting any television setting.
- *Progrommable Channel Blanking:* provides a means to force the picture to be blanked without affecting the audio. Perfect for audio-only services (e.g. FM radio).
- *Volume Control Locking Feature:* this feature forces the TV set to operate within a user defined volume range preventing volume adjustments.
- *Switch On Channel:* it forces the television to a specified channel when turned on. Perfect for in-house advertising or information channels.

Multi Longuoge Teletext reception with Lockout option
Guests can be served in their own teletext language. For each channel Western/ Eastern European, Turkish, Greek, Cyrillic or Arabic characters are available.
Teletext Lockout option to simply block all access to teletext information.

Auto Power On
Forces the default power setting to the ON position after a power interruption or preventing sets from being turned off while in use.

Audio/Video Muting
Automatically detects a loss of television signal and optionally mutes both audio and video.

Electronic Progrom Guide
Provides guest with onscreen directory listing number and network affiliation. Channel guide is accessed via the touch of a single button on the remote control.

ESP™ (Energy Soving Programmobility)
Energy Saving system that powers television off after a specified period of use. A simple countdown clock can be selectively set to operate from 0-99 hours with automatic clock reset at each power up.

Low Battery detection Remote Control
This feature informs hotelier the need to replace RC batteries to pre-empt guest complain.

Externol Speoker connection
Easy installation of speaker to bathroom via rear connector.

Welcome Messoge
A welcome greeting (max. 2 line with 20 characters each) is displayed on the screen each time the set is switched on.

Consumer Television Convertible
Easily converts to true consumer television for after-market sales.

UIR-Link+ 14HT3304
Makes it possible to connect a Set-top box to the tv and let the STB control the tv. Tamperproof, allows PREVIEW function, no tuner required in the STB, one remote control STB and tv.

Multiple Remote Control support
The tv can be easily configured to listen to 1 of 4 different remote controls. Allows the simultaneous use of up to 4 tvs in a single room.

RC2BB5/01

Type	Version	Transmission System	Destination
14HT3154-14HT3304	/01	PAL BG, SECAM L/L', PAL-I, BG/DK	Continental W. Europe + Eastern Europe + UAE
14HT3154-14HT3304	/05	PAL-I, SECAM L/L' PAL BG	United Kingdom + Ireland

Specifications subject to chonge without notice.

PHILIPS

Downloaded from www.Manualslib.com manuals search engine